

75  
Watt

  
CV

PF  
λ ≥ 0,96

IP 20

CE

EMC

M

M

F

ta-10°÷+40°C






  
84 mm

  
Dimmable

  
DMX  
Dimmable

  
DALI  
Dimmable



| Part Number  | Protocol              | Output<br>V | Output@230V<br>I max 3ch | Output@230V<br>I max 4ch | W<br>@230V | W<br>@110V | Dimensions<br>A x B x C |
|--------------|-----------------------|-------------|--------------------------|--------------------------|------------|------------|-------------------------|
| A40RGBOX412B | DALI DT6 / DMX / PUSH | 12V         | 3 x 2,08A                | 4 x 1,56A                | 75W        | 60W        | 210 x 75 x 35           |



Datasheet download



Instruction download

**Convertitori per LED RGBW a 4 canali e RGB a 3 canali a 12V**

- Alimentatore indipendente - IP20 - Classe II di isolamento
- Ingresso pulsante bassa tensione. Comando della luce - accensione, regolazione e spegnimento con uno o più pulsanti
- Ingresso DMX e DALI con funzione auto-test incorporata e LED di segnalazione
- Configurabile per 3 o 4 canali di uscita
- Per LED di potenza RGBW e RGB a tensione costante. Uscita 4 x 12V PWM o 3 x 12V PWM 300Hz. Anodo comune.
- Collegamento in parallelo fino a max 10 x RGBox4
- Doppio morsetto
- Morsetti rapidi
- Pressacavo adatto a vari tipi di cavo, sia tondi che piatti
- Alimentazione: 110÷240 V/AC - Uscita stabilizzata
- A richiesta, alimentazione specifica a 110V (uscita potenziata)

**12V driver for R G B W 4 channel and RGB 3 channel systems**

- Independent driver - IP20 - Insulation class II
- Low voltage push button input. Light control - on, off and colour regulation by one or more push-buttons
- DMX and DALI inputs with self-test function and LED signal
- Configuration for 3 or 4 output channels
- Suitable for RGBW systems and constant voltage RGB systems. Output 4 x 12V PWM or 3 x 12V PWM 300Hz. Common anode
- Possible parallel connection up to 10 x RGBOX4 drivers
- Double terminal block
- Fast terminals
- Cable clamp for flat and round cables
- Input voltage: 110÷240 V/AC - Steady output.
- On request, specific boosted 110V version